

Specification

Gemini AC/DC energisers (12v/220v adaptor)

Ever torn between the portability of a battery powered fence energiser and the hassle free reliability of a mains powered unit? The Gemini range of energisers, will run from either a 12v battery or from a mains power supply, perfect for those wanting to make the transition from a temporary, portable fence to a low maintenance mains system without the expense of purchasing two energisers. This is ideal if you wish to 'future proof' the fence and envisage shifting from temporary to a more permanent installation and for those needing to move small poultry systems around their land where power requirements change. The units come with earth, fence and battery leads and 12v mains adaptor; it can be mounted on either a wall or wooden post or hangs neatly on the Hotline ES2 earth stake.

- 12V input
- Mains adaptor
- Low battery indicator
- Hands on wall, post or earth stake



Model

○ 47HLC40

0.8j	0.45j	7.5kv	3.9kv	8km	1.2w	3	5	

Guide only. Line efficiency dependent on specification and an appropriate earth system.

○ 47HLC80

1.2j	0.8j	8.5kv	4.2kv	12km	1.6w	4	10	

Guide only. Line efficiency dependent on specification and an appropriate earth system.

○ 47HLC120

2.4j	1.2j	8.1kv	4.8kv	18km	2.6w	5	15	

Guide only. Line efficiency dependent on specification and an appropriate earth system.



For 110-240v Mains operation

Legend

- Stored/input Joule
- max. output joule
- max. volts
- volts under load*
- Approx max. distance
- Consumption (220v)
- Battery life
- no. Close pitch nets (eg. poultry)
- no. Wide pitch nets (eg. sheep)